

SCTE • ISBE[®]

S T A N D A R D S

Network Operations Subcommittee

AMERICAN NATIONAL STANDARD

ANSI/SCTE 85-4 2017

**HMS Common Inside Plant
Management Information Base(MIB)
SCTE-HMS-HE-OPTICAL-SWITCH-MIB**

NOTICE

The Society of Cable Telecommunications Engineers (SCTE) / International Society of Broadband Experts (ISBE) Standards and Operational Practices (hereafter called “documents”) are intended to serve the public interest by providing specifications, test methods and procedures that promote uniformity of product, interchangeability, best practices and ultimately the long-term reliability of broadband communications facilities. These documents shall not in any way preclude any member or non-member of SCTE•ISBE from manufacturing or selling products not conforming to such documents, nor shall the existence of such standards preclude their voluntary use by those other than SCTE•ISBE members.

SCTE•ISBE assumes no obligations or liability whatsoever to any party who may adopt the documents. Such adopting party assumes all risks associated with adoption of these documents, and accepts full responsibility for any damage and/or claims arising from the adoption of such documents.

Attention is called to the possibility that implementation of this document may require the use of subject matter covered by patent rights. By publication of this document, no position is taken with respect to the existence or validity of any patent rights in connection therewith. SCTE•ISBE shall not be responsible for identifying patents for which a license may be required or for conducting inquiries into the legal validity or scope of those patents that are brought to its attention.

Patent holders who believe that they hold patents which are essential to the implementation of this document have been requested to provide information about those patents and any related licensing terms and conditions. Any such declarations made before or after publication of this document are available on the SCTE•ISBE web site at <http://www.scte.org>.

All Rights Reserved

© Society of Cable Telecommunications Engineers, Inc. 2017

140 Philips Road

Exton, PA 19341

CONTENTS

SCOPE	4
COPYRIGHT	4
NORMATIVE REFERENCE	4
INFORMATIVE REFERENCE	4
TERMS AND DEFINITIONS	4
REQUIREMENTS	4

SCOPE

This document is identical to SCTE 85-4 2009 except for informative components which may have been updated such as the title page, NOTICE text, headers and footers. No normative changes have been made to this document.

This document provides MIB definitions for HMS optical switch equipment present in the headend (or indoor) and is supported by a SNMP agent.

COPYRIGHT

The MIB definition found in this document may be incorporated directly in products without further permission from the copyright owner, SCTE.

NORMATIVE REFERENCE

IETF RFC 1907 SNMPv2-MIB
IETF RFC 2578 SNMPv2-SMI
IETF RFC 2579 SNMPv2-TC
IETF RFC 2580 SNMPv2-CONF
IETF RFC 2737 ENTITY-MIB
SCTE 36 SCTE-ROOT
SCTE 37 SCTE-HMS-ROOTS
SCTE 38-11 SCTE-HMS-HEADENDIDENT-MIB
SCTE 83-1 SCTE-HMS-HE-OPTIC-MIB
SCTE 38-1 SCTE-HMS-HE-PROPERTY-MIB
SCTE 84-1 SCTE-HMS-HE-COMMON-MIB

INFORMATIVE REFERENCE

None

TERMS AND DEFINITIONS

This document defines the following terms:

Management Information Base (MIB) – the specification of information in a manner that allows standard access through a network management protocol.

REQUIREMENTS

This section defines the mandatory syntax of the SCTE-HMS-HE-OPTICAL-SWITCH-MIB. It follows the IETF Simple Network Management Protocol (SNMP) for defining managed objects.

The syntax is given below.

SCTE-HMS-HE-OPTICAL-SWITCH-MIB DEFINITIONS ::= BEGIN

IMPORTS

MODULE-COMPLIANCE, OBJECT-GROUP
 FROM SNMPv2-CONF
 OBJECT-TYPE, MODULE-IDENTITY, Unsigned32, Integer32
 FROM SNMPv2-SMI
 DisplayString
 FROM SNMPv2-TC
 entPhysicalIndex
 FROM ENTITY-MIB
 HeFaultStatus, HeHundredthNanoMeter,
 HeTenthdB, HeTenthdBm, HeOnOffControl
 FROM SCTE-HMS-HEADENDIDENT-MIB
 heOpticalSwitchGroup
 FROM SCTE-HMS-HE-OPTICS-MIB;

heOpticalSwitchMIB MODULE-IDENTITY

LAST-UPDATED "200310090000Z" -- Oct 9, 2003
 ORGANIZATION "SCTE HMS Working Group"
 CONTACT-INFO
 "SCTE HMS Subcommittee, Chairman
 mailto: standards@SCTE.org"

DESCRIPTION

"The MIB module for the HMS HE Optical Switch module entities.

This MIB module is for representing optical switch equipment present in the headend (or indoor) and is supported by a SNMP agent.

This MIB is limited in its scope and intended to describe an A-B (2 input and 1 output) or a crossbar optical switch. Up to 2 optical inputs and 2 outputs are supported. Any devices with more than 2 optical inputs or outputs shall be covered by another MIB.

This MIB does not intend to dictate all of the nuances involved in changing control settings (automatic or manual mode, changing switch controls in each possible mode combination). The most common desired behaviors are noted but specific switch operation and behavior are left to the optical switch vendors.

Not all control enumerations must be supported. This is noted in the variables that have optional enumerations.

Refer to the associated notes for information on what SNMP responses should be returned for unsupported enumerations."

::= { heOpticalSwitchGroup 1 }

heOpSwitchMIBObjects OBJECT IDENTIFIER ::= { heOpticalSwitchMIB 1 }

-- Every optical switch is modeled by the tables presented
 -- in this MIB module. These tables extend the entPhysicalTable
 -- according to RFC 2737. The extension index entPhysicalIndex uniquely
 -- identifies the optical switch.

-- Every optical switch is also modeled by the following tables:
 -- entPhysicalEntry - 1 row; (defined in document: RFC2737)
 -- heCommonEntry - 1 row. (defined in document: HMS111)

-- Every optical switch module will have its alarms modeled by the table:
 -- propertyEntry - x rows; (defined in document: HMS026)
 -- (where x is the nos. of alarmable analog properties supported
 -- by the optical switch)

-- discretePropertyEntry - y rows; (defined in document: HMS026)
 -- (where y is the nos. of alarmable digital properties supported by
 -- the optical switch)

-- Every optical switch module will have a list of currently active
 -- alarms modeled by the table:
 -- currentAlarmEntry - z rows; (defined in document: HMS026)
 -- (where z is the nos. of current active alarms in the optical
 -- switch)

-- Thus, an A-B optical switch (2 optical inputs and one optical output)
 -- will be represented by one row in entPhysicalTable, one row in
 -- heCommonTable, one row in heOpSwitchUnitTable, two rows in
 -- heOpSwitchInputTable and one row in heOpSwitchOutputTable.

-- Additionally, a crossbar optical switch (2 inputs and 2 outputs)
 -- will be represented by one row in entPhysicalTable, one row in
 -- heCommonTable, one row in heOpSwitchUnitTable, two rows
 -- in heOpSwitchInputTable and two rows in heOpSwitchOutputTable.

-- Correlation of outputs and inputs are indicated by the heOpSwitchState
 -- variable. Correlation of physical inputs and outputs to
 -- heOpSwitchInputTable and heOpSwitchOutputTables rows is indicated
 -- by the heOpSwitchInputDescription and heOpSwitchOutputDescription
 -- variables.

-- the Optical Switch Unit Table
 heOpSwitchUnitTable OBJECT-TYPE
 SYNTAX SEQUENCE OF HeOpSwitchUnitEntry
 MAX-ACCESS not-accessible
 STATUS current
 DESCRIPTION
 "A table containing information about Optical Switch used
 in an indoor environment."
 ::= { heOpSwitchMIBObjects 1 }

heOpSwitchUnitEntry OBJECT-TYPE

is in manual mode and the operator tries to connect the output to an invalid input, the switch may or may not change state.

Not all enumerations must be supported. For example, an A-B optical switch may support only the pathA and pathB enumerations while a cross-bar switch may support cross, bar, bothA or bothB or only cross and bar but not pathA and pathB enumerations. See the note below about the expected SNMP response.

A value pathA(1) connects the switch output to side A (first input) of the switch. This enumeration is intended for use by an A-B switch.

A value pathB(2) connects the switch output to side B (second input) of the switch. This enumeration is intended for use by an A-B switch.

A value cross(3) connects the switch outputs to the inputs as follows:
Side A (first or primary) output is connected to side B (second or alternate) input.
Side B (second or alternate) output is connected to side A (first or primary) input.
This enumeration is intended for use by a cross-bar switch.

A value bar(4) connects the switch outputs to the inputs as follows:
Side A (first or primary) output is connected to side A (first or primary) input.
Side B (second or alternate) output is connected to side B (second or alternate) input.
This enumeration is intended for use by a cross-bar switch.

A value bothA(5) connects the switch outputs to the inputs as follows:
Side A (first or primary) output is connected to side A (first or primary) input.
Side B (second or alternate) output is connected to side A (first or primary) input.
This enumeration is intended for use by a cross-bar switch.

A value bothB(6) connects the switch outputs to the inputs as follows:
Side A (first or primary) output is connected to side B (second or alternate) input.
Side B (second or alternate) output is connected to side B (second or alternate) input.
This enumeration is intended for use by a cross-bar switch.

***** IMPORTANT *****

It is NOT required that an optical switch support all enumerations. A SET request for an unsupported value shall yield a badValue(3) error by an SNMPv1 agent or an inconsistentValue(12) by an SNMPv2 agent."

```
::= { heOpSwitchUnitEntry 2 }
```

heOpSwitchRevertEnable OBJECT-TYPE

```
SYNTAX      HeOnOffControl
MAX-ACCESS  read-write
STATUS      current
DESCRIPTION
```

"This controls the use of revertive switching.

If set to on, the switch will attempt to go back to the preferred settings indicated by heOpSwitchControl if heOpSwitchMode is set to automatic, and the input status of the preferred input is normal. The switch will not attempt to revert to the settings indicated by heOpSwitchControl until heOpSwitchWaitToRestoreTime (if supported) has expired since the preferred input was restored to normal levels.

If set to off, the switch will not attempt to go back to the preferred settings indicated by heOpSwitchControl if heOpSwitchMode is set to automatic, and the input status of the preferred input is normal.

"

```
::= { heOpSwitchUnitEntry 3 }
```

heOpSwitchState OBJECT-TYPE

```
SYNTAX      INTEGER {
    pathA(1),
    pathB(2),
                cross(3),
                bar(4),
                bothA(5),
                bothB(6)
}
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
```

"Reports the state of the Optical Switch. Not all enumerations must be supported. For example, an A-B optical switch may support only the pathA and pathB enumerations while a cross-bar switch may support cross, bar, bothA or bothB or only cross and bar but not pathA and pathB enumerations.

A value pathA(1) indicates that the switch output is being fed by side A (first input) of the switch. This enumeration is intended for use by an A-B switch.

A value pathB(2) indicates that the switch output is being fed by side B (second input) of the switch. This enumeration is intended for use by an A-B switch.

A value cross(3) indicates that the switch outputs are fed as follows:
Side A (first or primary) output is connected to side B (second or alternate) input.
Side B (second or alternate) output is connected to side A (first or primary) input.
This enumeration is intended for use by a cross-bar switch.

A value bar(4) indicates that the switch outputs are fed as follows:
Side A (first or primary) output is connected to side A (first or primary) input.
Side B (second or alternate) output is connected to side B (second or alternate) input.
This enumeration is intended for use by a cross-bar switch.

A value bothA(5) indicates that the switch outputs are fed as follows:
Side A (first or primary) output is connected to side A (first or primary) input.
Side B (second or alternate) output is connected to side A (first or primary) input.
This enumeration is intended for use by a cross-bar switch.

A value bothB(6) indicates that the switch outputs are fed as follows:
Side A (first or primary) output is connected to side B (second or alternate) input.
Side B (second or alternate) output is connected to side B (second or alternate) input.
This enumeration is intended for use by a cross-bar switch."

::= { heOpSwitchUnitEntry 4 }

heOpSwitchFailoverStatus OBJECT-TYPE

SYNTAX HeFaultStatus

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The integral status of both inputs.

A value is fault(2), if current switch state heOpSwitchState is different than the preferred setting heOpSwitchControl, otherwise, it is normal(1).

This object must provide for the alarm management capabilities with a corresponding entry in the discretePropertyTable of SCTE-HMS-PROPERTY-MIB (HMS026).

An alarm shall be recorded as an entry in the currentAlarmTable of SCTE-HMS-PROPERTY-MIB (HMS026).

A log record shall be added as an entry in the heCommonLogTable.

An heCommonAlarmEvent notification shall be sent."

::= { heOpSwitchUnitEntry 5 }

heOpSwitchBothInputStatus OBJECT-TYPE

SYNTAX HeFaultStatus

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The integral status of both inputs.

A value is fault(2), if both input levels are below the nominal value; otherwise, it is normal(1).

This object must provide for the alarm management capabilities with a corresponding entry in the discretePropertyTable of SCTE-HMS-PROPERTY-MIB (HMS026).

An alarm shall be recorded as an entry in the currentAlarmTable of SCTE-HMS-PROPERTY-MIB (HMS026).

A log record shall be added as an entry in the heCommonLogTable.

An heCommonAlarmEvent notification shall be sent."

::= { heOpSwitchUnitEntry 6 }

heOpSwitchSelectWavelength OBJECT-TYPE

SYNTAX HeHundredthNanoMeter

UNITS "0.01 nm"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"Wavelength feeding the particular input of the optical switch.

Typical values might be 131000 (1310 nm) and 155000 (1550 nm)."

::= { heOpSwitchUnitEntry 7 }

heOpSwitchHysteresis OBJECT-TYPE

SYNTAX HeTenthdB (-20..20)

UNITS "0.1 dB"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"Controls switch input hysteresis amount. The amount of hysteresis used and the ability to change it is to be determined by the vendor."

::= { heOpSwitchUnitEntry 8 }

heOpSwitchWaitToRestoreTime OBJECT-TYPE

SYNTAX Integer32

UNITS "1 sec"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"Controls hysteresis time in sec.

If in automatic switching mode and revert mode is enabled,

a switch back to the original side will be delayed for
the time specified by this object."

::= { heOpSwitchUnitEntry 9 }

-- the Optical Switch Input Table

heOpSwitchInputTable OBJECT-TYPE

SYNTAX SEQUENCE OF HeOpSwitchInputEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A table containing information about each Optical Switch
input used in an indoor environment."

::= { heOpSwitchMIBObjects 2 }

heOpSwitchInputEntry OBJECT-TYPE

SYNTAX HeOpSwitchInputEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"List of information about each optical switch input."

INDEX { entPhysicalIndex, heOpSwitchInputIndex }

::= { heOpSwitchInputTable 1 }

HeOpSwitchInputEntry ::= SEQUENCE

```
{
  heOpSwitchInputIndex          Unsigned32,
  heOpSwitchInputOpticalLevel   HeTenthdBm,
  heOpSwitchSetInputPowerThreshold HeTenthdBm,
  heOpSwitchInputStatus        HeFaultStatus,
  heOpSwitchInputDescription    DisplayString
}
```

heOpSwitchInputIndex OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"Index number corresponding to the Optical Input."

::= { heOpSwitchInputEntry 1 }

heOpSwitchInputOpticalLevel OBJECT-TYPE

SYNTAX HeTenthdBm

UNITS "0.1 dBm"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The measured optical input power for the optical switch."

::= { heOpSwitchInputEntry 2 }

heOpSwitchSetInputPowerThreshold OBJECT-TYPE

SYNTAX HeTenthdBm

UNITS "0.1 dBm"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"Input power switchover point for this input."
 ::= { heOpSwitchInputEntry 3 }

heOpSwitchInputStatus OBJECT-TYPE

SYNTAX HeFaultStatus

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The integral status of the input.

A value is fault(2), if the input levels are not in the nominal range; otherwise, it is normal(1).

This object must provide for the alarm management capabilities with a corresponding entry in the discretePropertyTable of SCTE-HMS-PROPERTY-MIB (HMS026).

An alarm shall be recorded as an entry in the currentAlarmTable of SCTE-HMS-PROPERTY-MIB (HMS026).

A log record shall be added as an entry in the heCommonLogTable.

An heCommonAlarmEvent notification shall be sent."

::= { heOpSwitchInputEntry 4 }

heOpSwitchInputDescription OBJECT-TYPE

SYNTAX DisplayString (SIZE (0..32))

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A description of the switch input. The description text is to be determined by the equipment manufacturer. For example, Input A or Side B."

::= { heOpSwitchInputEntry 5 }

-- the Optical Switch Output Table

heOpSwitchOutputTable OBJECT-TYPE

SYNTAX SEQUENCE OF HeOpSwitchOutputEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A table containing information about each Optical Switch output used in an indoor environment."

::= { heOpSwitchMIBObjects 3 }

heOpSwitchOutputEntry OBJECT-TYPE

SYNTAX HeOpSwitchOutputEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"List of information about each optical switch output."

INDEX { entPhysicalIndex, heOpSwitchOutputIndex }

```

 ::= { heOpSwitchOutputTable 1 }

HeOpSwitchOutputEntry ::= SEQUENCE
{
  heOpSwitchOutputIndex      Unsigned32,
  heOpSwitchOutputDescription  DisplayString
}

heOpSwitchOutputIndex OBJECT-TYPE
  SYNTAX      Unsigned32
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "Index number corresponding to the Optical Output."
  ::= { heOpSwitchOutputEntry 1 }

heOpSwitchOutputDescription OBJECT-TYPE
  SYNTAX      DisplayString (SIZE (0..32))
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "A description of the switch output. The description text is
    to be determined by the equipment manufacturer. For example,
    Output A or Secondary Output."
  ::= { heOpSwitchOutputEntry 2 }

-- conformance information
heOpSwitchMIBConformance OBJECT IDENTIFIER ::= { heOpticalSwitchMIB 2 }

heOpSwitchMIBCompliances OBJECT IDENTIFIER ::= { heOpSwitchMIBConformance 1 }

heOpSwitchMIBGroups      OBJECT IDENTIFIER ::= { heOpSwitchMIBConformance 2 }

heOpSwitchBasicCompliance MODULE-COMPLIANCE
  STATUS      current
  DESCRIPTION
    "The compliance statement for SNMP HMS Headend Optical
    Switch entities which implement the SNMP
    heOpticalSwitchMIB."
  MODULE -- this module
    MANDATORY-GROUPS { heOpSwitchUnitMandatoryGroup,
                       heOpSwitchInputMandatoryGroup,
                       heOpSwitchOutputMandatoryGroup
    }

  ::= { heOpSwitchMIBCompliances 1 }

heOpSwitchUnitMandatoryGroup OBJECT-GROUP
  OBJECTS {
    heOpSwitchMode,
    heOpSwitchControl,
    heOpSwitchState,
    heOpSwitchFailoverStatus

```

```

    }
    STATUS current
    DESCRIPTION
        "The main group defines heOpSwitchUnitTable objects which
         are mandatory to all indoor optical switch modules."
    ::= { heOpSwitchMIBGroups 1 }

```

```

heOpSwitchInputMandatoryGroup OBJECT-GROUP
    OBJECTS {
        heOpSwitchInputStatus,
        heOpSwitchInputDescription
    }
    STATUS current
    DESCRIPTION
        "The main group defines heOpSwitchInputTable objects which
         are mandatory to all indoor optical switch modules."
    ::= { heOpSwitchMIBGroups 2 }

```

```

heOpSwitchOutputMandatoryGroup OBJECT-GROUP
    OBJECTS {
        heOpSwitchOutputDescription
    }
    STATUS current
    DESCRIPTION
        "The main group defines heOpSwitchOutputTable objects which
         are mandatory to all indoor optical switch modules."
    ::= { heOpSwitchMIBGroups 3 }

```

```

heOpSwitchUnitGroup OBJECT-GROUP
    OBJECTS {
        heOpSwitchRevertEnable,
        heOpSwitchBothInputStatus,
        heOpSwitchSelectWavelength,
        heOpSwitchHysteresis,
        heOpSwitchWaitToRestoreTime
    }
    STATUS current
    DESCRIPTION
        "The collection of heOpSwitchUnitTable objects which are used to
         represent the indoor optical switch module."
    ::= { heOpSwitchMIBGroups 4 }

```

```

heOpSwitchInputGroup OBJECT-GROUP
    OBJECTS {
        heOpSwitchInputOpticalLevel,
        heOpSwitchSetInputPowerThreshold
    }
    STATUS current
    DESCRIPTION
        "The collection of heOpSwitchInputTable objects which are used to
         represent the indoor optical switch module."
    ::= { heOpSwitchMIBGroups 5 }

```

END